

DID YOU KNOW SALES TIPS

From

DSC®

Power Series V4.2 Now Supports Seven Step Template Programming

Template programming allows quick programming of the minimum functions required for basic control panel operation in a seven step programming sequence. This feature requires a PK55XX or RFK55XX series keypad, v.1.1 or higher.

Selecting [*][8] [Installer Code] [899] displays the current 5 digit template programming code. Each digit represents 1 of the template sections listed below. The option number selected for each digit will make up the 5 digit template programming code.

- Digit 1** selects Zone 1-8 definition options. *Refer to Appendix E: Template programming in the Control Panel's Installation Manual for all options for the 5 separate digits*
- Digit 2** selects system EOL configuration options.
- Digit 3** selects panel communications options.
- Digit 4** selects reporting code configurations.
- Digit 5** selects DLS connection options.

After entering a valid 5 digit template programming code, you will be prompted to enter the following in the sequence indicated below:

- Central Station Telephone Number (Section 301)
Program the required Central Station phone number. Press [#] to complete your entry if less than 32 digits.
- Central Station Account Code, enter 6-digit code (Section 310)
Program the required Central Station Account Code. Press [#] to complete your entry if less than 6 digits.
- Partition Account Code, enter 4-digit code (Section 311)
This programming section will only be prompted if Contact ID has been selected as a communications format. Program the required partition Account Code.
- DLS Access Code, enter 6-digit code (Section 403)
Program the required DLS Access Code. Press [#] to complete your entry if less than 6 digits.
- Partition 1 Entry Delay 1, Partition 1 Exit Delay (Section 005 subsection [01])
Program the desired 3 digit Partition 1 Entry Delay (in seconds) followed by the desired 3 digit Partition 1 Exit Delay (in seconds).
- Installers Code (Section 006)
Enter the required 4 digit installers code. After the Installers Code has been programmed the keypad will return to base installers programming menu.